

# Product data sheet

Specifications

## Load center interior, QO, mounting base, 1 phase, 2 spaces, 70A main lugs, OEM



QON2L70

**Product availability: Stock - Normally stocked in distribution facility**

### Main

Product Type	Mounting base
Marketing Trade Name	QO
Load Center Type	Main lugs
Rated Current	70 A
Number of Spaces	2
Max Short Circuit Current Rating	10 kA
Number of Phases	1 phase 2 wires
Voltage Rating	120/240 V AC

### Complementary

Wire Size	AWG 14...AWG 4 copper AWG 12...AWG 3 aluminium
Product Certifications	UL CSA
Height	2.7 in (69 mm)
Width	4.2 in (107 mm)
Depth	1.9 in (48 mm)
Net Weight	1.543 lb(US) (0.700 kg)

### Ordering and shipping details

Category	US1DE3A00909
Discount Schedule	DE3A
GTIN	785901029410
Returnability	Yes
Country of origin	MX

### Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.00 in (5.08 cm)
Package 1 Width	2.80 in (7.112 cm)
Package 1 Length	4.30 in (10.922 cm)
Package weight(Lbs)	2.240 oz (63.503 g)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

# Contractual warranty

---

Warranty

18 months

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

California proposition 65

WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

## Use Again

### Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No

Technical Illustration

Dimensions

---