

# Product data sheet

Specifications



## Disconnect switch, TeSys VLS, additional pole, 40A, for 16A to 40A switch, size 1, DIN rail

VLS1P040R1S

**Product availability: Stock - Normally stocked in distribution facility**

### Main

Range	TeSys
Device short name	VLS1P
Product or Component Type	Additional pole
Performance level	High performance
Poles description	1P
Contacts type and composition	1 NO
Contact operation	Simultaneous
Range compatibility	TeSys TeSys VARIO LS VLS3P
Network type	AC
Network Frequency	50/60 Hz
Suitability for isolation	Yes

### Complementary

Mounting Location	Left Right
Mounting Support	DIN rail
[Ue] rated operational voltage	690 V AC 50/60 Hz
[Uimp] rated impulse withstand voltage	8 kV
[Ith] conventional free air thermal current	40 A (at 131 °F (55 °C))
[Ithe] conventional enclosed thermal current	40 A
[Ie] rated operational current	40 A Ue: 600 V UL 508 40 A AC-21A Ue: 400 V 40 A AC-21A Ue: 500 V 40 A AC-21A Ue: 690 V 40 A AC-22A Ue: 400 V 40 A AC-22A Ue: 500 V 40 A AC-22A Ue: 690 V 40 A AC-23A Ue: 400 V 25 A AC-23A Ue: 500 V 25 A AC-23A Ue: 690 V
Rated operational power in W	18.5 kW 400 V AC-23A) 18.5 kW 500 V AC-23A) 22 kW 690 V AC-23A)
Intermittent duty class	Class 120 - 60 %
Making capacity ( I Rms)	60 A 690 V AC-21A 120 A 690 V AC-22A 400 A 690 V AC-23A

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

<b>[Icm] rated short-circuit making capacity</b>	1128 A 690 V
<b>[Icw] rated short-time withstand Rms current</b>	800 A 690 V 1 s
<b>Rated conditional short-circuit current</b>	50 kA 400 V 40 A gG
<b>Breaking capacity</b>	60 A 690 V AC-21A) 120 A 690 V AC-22A) 320 A 690 V AC-23A)
<b>Mechanical durability</b>	100000 cycles
<b>Electrical durability</b>	100000 cycles AC-21A
<b>Connections - terminals</b>	Power circuit screw clamp terminals 0.02 in <sup>2</sup> (10 mm <sup>2</sup> ) solid Power circuit screw clamp terminals 0.02 in <sup>2</sup> (16 mm <sup>2</sup> ) flexible - without cable end
<b>Tightening torque</b>	Power circuit 15.9...17.7 lbf.in (1.8...2 N.m) screw clamp terminals
<b>Height</b>	3.07 in (78 mm)
<b>Width</b>	0.5 in (12 mm)
<b>Depth</b>	1.7 in (43.6 mm)
<b>Net Weight</b>	0.09 lb(US) (0.04 kg)
<b>color</b>	Gray

## Environment

<b>Standards</b>	UL 508 CSA C22.2 No 14 IEC 60947-3
<b>Product Certifications</b>	cULus GL
<b>IP degree of protection</b>	IP20 conforming to IEC 60529
<b>Mechanical robustness</b>	Vibrations 2...100 Hz Fc 0.7 g) IEC 60068-2-6 Shocks 11 ms Ea 15 gn) IEC 60068-2-27
<b>Ambient Air Temperature for Operation</b>	-13...131 °F (-25...55 °C)
<b>Fire resistance</b>	1760 °F (960 °C) IEC 60695-2-11

## Ordering and shipping details

<b>Category</b>	US10CP121734
<b>Discount Schedule</b>	0CP1
<b>GTIN</b>	3606481156594
<b>Returnability</b>	Yes
<b>Country of origin</b>	IT

## Packing Units

<b>Unit Type of Package 1</b>	PCE
<b>Nbr. of units in pkg.</b>	1
<b>Package 1 Height</b>	1.26 in (3.200 cm)
<b>Package 1 Width</b>	2.76 in (7.000 cm)
<b>Package 1 Length</b>	3.23 in (8.200 cm)
<b>Package weight(Lbs)</b>	1.517 oz (43.000 g)
<b>Unit Type of Package 2</b>	S01

<b>Number of Units in Package 2</b>	30
<b>Package 2 Height</b>	5.91 in (15.000 cm)
<b>Package 2 Width</b>	5.91 in (15.000 cm)
<b>Package 2 Length</b>	15.75 in (40.000 cm)
<b>Package 2 Weight</b>	3.278 lb(US) (1.487 kg)

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Compliant
California proposition 65	<b>WARNING:</b> This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No