

Product data sheet

Specifications

SQUARE D



Operating mechanism, flange mounted, variable depth, 30A, 600V, no fuse, cable operated switch mechanism

9422TCN30C

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Range	9422T
Product	Disconnect Switch
Disconnect Type	Non-fusible disconnect switch

Complementary

Mounting Type	Flange cable variable depth
Current Rating	30 A
Horsepower Rating	7.5 hp 200 V AC 7.5 hp 230 V AC 15 hp 460 V AC 20 hp 575 V AC 5 hp 250 V DC
Handle Type	Ordered separately

Environment

Certifications	CSA UL Recognized
----------------	----------------------

Ordering and shipping details

Category	US10CP121732
Discount Schedule	0CP1
GTIN	785901697190
Returnability	No
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	7.50 in (19.05 cm)
Package 1 Width	11.00 in (27.94 cm)
Package 1 Length	16.50 in (41.91 cm)
Package weight(Lbs)	9.780 lb(US) (4.436 kg)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Warranty

18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Take-back	No