



Meter center, MP Meter-Pak, 3 sockets, no bypass, 4 jaws, 300A bus, 125A max breaker rating, ringed

MP33125

Product availability: Stock - Normally stocked in distribution facility

#### Main

Product	Meter Center
Socket Rating	125 A
Main Type	Main Lugs
Number of Jaws	4
Number of Meter Sockets	3
Socket Type	Ringed

## Complementary

300 A	
300 A	
UL Listed	
Meter-Pak	
Aluminium: busbar	
No bypass	
Steel	
NEMA 3R	
120/240 V AC	
Surface	
1 phase	
UG OH	
AWG 1/0600 kcmil 1 aluminium AWG 1/0600 kcmil 1 copper	
3-wire	
48.12 in (1222.25 mm)	
24.34 in (618.24 mm)	
7.28 in (184.91 mm)	

## Ordering and shipping details

Category	US10DE400021
Discount Schedule	0DE4

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

GTIN	785901001799	
Returnability	Yes	
Country of origin	MX	

# **Packing Units**

Unit Type of Package 1	PCE	
Nbr. of units in pkg.	1	
Package 1 Height	8.5 in (21.6 cm)	
Package 1 Width	24.7 in (62.7 cm)	
Package 1 Length	49.02 in (124.5 cm)	
Package weight(Lbs)	88.930 lb(US) (40.338 kg)	

## **Contractual warranty**

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

#### **Use Better**


Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

### Use Again

○ Repack and remanufacture	
Take-back	No

## **Technical Illustration**

## **Dimensions**



**Technical Illustration** 

## Wiring diagram

