

Product data sheet

Specifications

SQUARE D



Mini circuit breaker accessory,
QO, lug kit, 125A, 3 pole, 3
spaces, subfeed

QO3125SL

Product availability: Stock - Normally stocked in distribution facility

Main

Product Type	Lug kit
Marketing Trade Name	QO
Rated Current	125 A
Number of Spaces	3
Number of Phases	3 phase
Voltage Rating	240 V AC

Complementary

Number of Poles	3
Wire Size	AWG 12...AWG 2/0 copper or aluminium
Product Certifications	CSA cURus
Mounting Mode	Plug-in
Height	3.500 in (88.900 mm)
Width	2.241 in (56.921 mm)
Depth	2.310 in (58.674 mm)

Environment

Ambient Air Temperature for Operation	23 °F (-5 °C) 104 °F (40 °C)
---------------------------------------	---------------------------------

Ordering and shipping details

Category	US1DE2A00081
Discount Schedule	DE2A
GTIN	785901031338
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.30 in (5.842 cm)
Package 1 Width	3.40 in (8.636 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package 1 Length	3.80 in (9.652 cm)
Package weight(Lbs)	14.080 oz (399.161 g)

Contractual warranty

Warranty	18 months
----------	-----------



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	Yes
EU RoHS Directive	Compliant
SCIP Number	Af42fb01-813d-40c0-ae28-b8b3299dbc99
REACH Regulation	REACH Declaration
Halogen content performance	Halogen free product

Use Again

Repack and remanufacture

Circularity Profile	No need of specific recycling operations
Take-back	No