

Switches and Lighting Control, Fluorescent Starter, 13-30-40W

By Hubbell Wiring Device-Kellems
Catalog # [FS4](#)

Switches and Lighting Control, Fluorescent Starter, 13-30-40W



Features

- Rugged construction
- Operates over a wide temperature range
- Neostart lights in dual lamp circuit uniformly and quickly

Specifications

| | |
|------------------------------------|-----------|
| EU RoHS Indicator | Yes |
| Standards - RoHS Compliance Status | CM |
| Industry Standard(s) | UL Listed |

Current

| | |
|------------------|-------------------------------|
| Frequency Rating | 60 Hz |
| Wattage | 4, 6 and 8 Watt Lamps |
| Voltage Rating | Determined by the ballasts kV |

Dimensions

| | |
|------------|--------------------------|
| Length | 1.5 in |
| Width | 0.7 in |
| Height | 0.7 in |
| Dimensions | 1.5 in x 0.7 in x 0.7 in |

General

| | |
|---|---|
| OEM Brand Name | Hubbell Wiring Device-Kellems |
| Color | Gray |
| Material - Mounting Hardware Specifications | Twist-In <ul style="list-style-type: none">• Product Type - Fluorescent Starters• Starter Wattage - 13, 30 and 40 watt lamps |
| Lamp Type | Fluorescent |
| UPC | 783585750033 |

Logistics

| | |
|-----------------|----|
| Carton Quantity | 25 |
|-----------------|----|

Operational

| | |
|------------|-----------|
| Start Type | Neo Start |
|------------|-----------|

Product Assets

- [Catalog \[English\]](#)
- [Catalog Page \[English\]](#)