## Blanking cover, Tesys Ultra, for auxiliary contact, communication or function module location LU9

LU9C1

## Main

| | |
|---|---|
| Range | TeSys |
| Device short name | LU9C |
| Product or component type | Blanking cover |

## Complementary

| | |
|---|---|
| Net weight | 0.022 kg |

## Packing Units

| | |
|---|---|
| Unit Type of Package 1 | PCE |
| Number of Units in Package 1 | 1 |
| Package 1 Height | 2.500 cm |
| Package 1 Width | 6.500 cm |
| Package 1 Length | 8.000 cm |
| Package 1 Weight | 22.000 g |
| Unit Type of Package 2 | S01 |
| Number of Units in Package 2 | 20 |
| Package 2 Height | 15.000 cm |
| Package 2 Width | 15.000 cm |
| Package 2 Length | 40.000 cm |
| Package 2 Weight | 619.000 g |

## Contractual warranty

| | |
|---|---|
| Warranty | 18 months |

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained 〉

How we assess product sustainability 〉

### Use Better

#### Materials and Substances

| | |
|---|---|
| Packaging made with recycled cardboard | **Yes** |
| Packaging without single use plastic | **No** |
| EU RoHS Directive | **Compliant** |
| REACh Regulation | **REACh Declaration** |

### Use Again

#### Repack and remanufacture

| | |
|---|---|
| Take-back | **No** |

Life Is On | Schneider Electric