

Product data sheet

Specifications



One entry cable gland plate,
PanelSeT SFN, PanelSeT SF, for
electrical enclosure W800 D400mm,
fixed by clips

NSYEC841

Main

Range	PanelSeT
Product or component type	Cable gland plate
Accessory / separate part category	Cable management accessory
Application	Multi-purpose
Range compatibility	PanelSeT PanelSeT SF SF
Mounting location	Enclosure bottom
Cable gland type	Standard
Cable entry	1 entry
Device composition	fixing elements 1 plate self extinguishing polyurethane adhesive gasket with cross-section of 15 x 25 mm
Quantity per set	Set of 1
Material	Galvanised steel

Complementary

Height	30 mm
Width	Nominal: 800 mm Useful: 616 mm Real: 650 mm
Depth	Nominal : 400 mm
thickness	1.5 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.000 cm
Package 1 Width	15.000 cm
Package 1 Length	65.500 cm
Package 1 Weight	2.900 kg
Unit Type of Package 2	P12
Number of Units in Package 2	50
Package 2 Height	40.000 cm
Package 2 Width	80.000 cm

Package 2 Length	120.000 cm
------------------	------------

Package 2 Weight	155.000 kg
------------------	------------

Contractual warranty

Warranty	18 months
----------	-----------



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Total lifecycle Carbon footprint 20

Environmental Disclosure [Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard No

Packaging without single use plastic No

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

SCIP Number 52da316e-d4e1-4114-85c0-32a03b2934fd

REACH Regulation [REACH Declaration](#)

Use Again

Repack and remanufacture

End of life manual availability No need of specific recycling operations

Take-back No