

# Product data sheet

Specifications



Reinforced coupling kit to carry heavy loads, PanelSeT SFN, PanelSeT SF, set of 4 connectors and fixing elements

NSYSFBKR

## Main

Range	PanelSeT
Accessory / separate part category	Coupling accessory
Product or component type	Coupling kit
Anwendung	Multi-purpose
Mounting location	Depthwise coupling of 2 enclosures Side coupling of 2 enclosures
Mounting support	Coupling kit
Range compatibility	PanelSeT SF suitable enclosure
Device composition	4 reinforced connector fixing elements
Quantity per set	Set of 1

## Complementary

Material	Steel
Surface finish	Zinc coated
Fixing mode	By screws - screw type M6 self tapping
Height	70 mm
Width	105 mm
Depth	150 mm

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	8.000 cm
Package 1 Width	12.000 cm
Package 1 Length	21.000 cm
Package 1 Weight	2.089 kg
Unit Type of Package 2	P12
Number of Units in Package 2	250
Package 2 Height	50.000 cm
Package 2 Width	80.000 cm
Package 2 Length	120.000 cm

---

Package 2 Weight	550.000 kg
------------------	------------

## Contractual warranty

---

Warranty	18 months
----------	-----------



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Total lifecycle Carbon footprint 15

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard No

Packaging without single use plastic No

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

SCIP Number 52da316e-d4e1-4114-85c0-32a03b2934fd

REACH Regulation [REACH Declaration](#)

## Use Again

### Repack and remanufacture

End of life manual availability No need of specific recycling operations

Take-back No