

Product data sheet

Specifications



Load center interior, QO, mounting base, 3 phase, 12 spaces, 125A main lugs, OEM, neutral busbar

QON312L125I

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product Type	Mounting base
Marketing Trade Name	QO
Load Center Type	Main lugs
Rated Current	125 A
Number of Spaces	12
Max Short Circuit Current Rating	10 kA
Number of Phases	3 phase 4 wires
Voltage Rating	120/240 V AC

Complementary

Wire Size	AWG 4...AWG 2/0 aluminium/copper
Product Certifications	UL Listed CSA
Height	9.6 in (244 mm)
Width	10.6 in (270 mm)
Depth	3.03 in (77 mm)
Net Weight	2.491 lb(US) (1.130 kg)

Ordering and shipping details

Category	US1DE3A00909
Discount Schedule	DE3A
GTIN	785901700555
Returnability	No
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.10 in (5.334 cm)
Package 1 Width	11.60 in (29.464 cm)
Package 1 Length	15.10 in (38.354 cm)
Package weight(Lbs)	10.0002 lb(US) (4.536 kg)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Contractual warranty

Warranty	18 months
----------	-----------

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint	
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No

Technical Illustration

Dimensions

Technical Illustration

Wiring diagram

