

Product data sheet

Specifications



protection module, Harmony
Electromechanical Relays, with RC
circuit, for all RUM sockets, 6...250V
DC

RUW241P7

Product availability: Stock - Normally stocked in distribution facility

Main

| | |
|---------------------------------------|--|
| Range of Product | Harmony Electromechanical Relays |
| Accessory / separate part category | Protection accessories |
| Product or Component Type | Protection module |
| Accessory / separate part designation | RC circuit |
| Product compatibility | Socket RPZ 3 C/O) Socket RPZ 4 C/O) Socket RUZ 2 C/O) Socket RUZ 3 C/O) |
| Product Destination | RPM relay RUM relay |
| [Uc] control circuit voltage | 110...240 V AC |
| Sale per indivisible quantity | 10 |

Complementary

| | |
|------------|-------------------------|
| Net Weight | 0.009 lb(US) (0.004 kg) |
|------------|-------------------------|

Ordering and shipping details

| | |
|-------------------|---------------|
| Category | US10CP221128 |
| Discount Schedule | 0CP2 |
| GTIN | 3389119403337 |
| Returnability | Yes |
| Country of origin | CN |

Packing Units

| | |
|------------------------------|--------------------|
| Unit Type of Package 1 | PCE |
| Nbr. of units in pkg. | 1 |
| Package 1 Height | 0.39 in (1.000 cm) |
| Package 1 Width | 1.36 in (3.450 cm) |
| Package 1 Length | 1.42 in (3.600 cm) |
| Package weight(Lbs) | 0.141 oz (4.000 g) |
| Unit Type of Package 2 | BB1 |
| Number of Units in Package 2 | 10 |

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

| | |
|-------------------------------------|-------------------------|
| Package 2 Height | 1.57 in (4.000 cm) |
| Package 2 Width | 3.15 in (8.000 cm) |
| Package 2 Length | 3.94 in (10.000 cm) |
| Package 2 Weight | 1.728 oz (49.000 g) |
| Unit Type of Package 3 | S01 |
| Number of Units in Package 3 | 300 |
| Package 3 Height | 5.91 in (15.000 cm) |
| Package 3 Width | 5.91 in (15.000 cm) |
| Package 3 Length | 15.75 in (40.000 cm) |
| Package 3 Weight | 4.156 lb(US) (1.885 kg) |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty | 18 months |
|-----------------|-----------|



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

| | |
|--|---|
| Carbon footprint (kg CO2 eq, Total Life cycle) | 1 |
|--|---|

Use Better

Materials and Substances

| | |
|--|-----|
| Packaging made with recycled cardboard | Yes |
|--|-----|

| | |
|--------------------------------------|----|
| Packaging without single use plastic | No |
|--------------------------------------|----|

| | |
|-----------------------------------|--|
| EU RoHS Directive | Pro-active compliance (Product out of EU RoHS legal scope) |
|-----------------------------------|--|

| | |
|------------------|-----------------------------------|
| REACH Regulation | REACH Declaration |
|------------------|-----------------------------------|

| | |
|---------------------------|---|
| California proposition 65 | WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov |
|---------------------------|---|

Use Again

Repack and remanufacture

| | |
|---------------------|--|
| Circularity Profile | No need of specific recycling operations |
|---------------------|--|

| | |
|-----------|----|
| Take-back | No |
|-----------|----|

| | |
|------|--|
| WEEE |  The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins. |
|------|--|

Connections and Schema

Wiring Diagram

