

# T36FN13G7

Starter, TeSys N, 135A, 100hp at 575VAC, 3 phase, NEMA size 4 at 120VAC



## Main

Product	Starter
Range of Product	TeSys N
Current Rating	135 A
Certifications	UL Listed[RETURN]CSA
Control Circuit Type	Common control circuit
Enclosure Type	Not rated (open device)
Auxiliary Contacts	1 NO
Horsepower Rating	40 HP 200 V AC 50 HP 230 V AC 100 HP 460 V AC 100 HP 575 V AC
Number of Poles	3P
Phase	3 phase
Maximum Voltage Rating	600 V AC
NEMA Size	4
Control Circuit Voltage	120 V AC
Starter Type	Non reversing
Electrical Connection	Lugs
Overload Type	Solid state Motor Logic class 10/20 45...135 A

## Ordering and shipping details

Category	US10CP121199
Discount Schedule	OCP1
GTIN	785901084969
Returnability	No
Country of origin	US

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	16.301 lb(US) (7.394 kg)

## Offer Sustainability

California proposition 65	WARNING: Cancer and Reproductive Harm - <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>
REACH Regulation	<a href="#">REACH Declaration</a>
REACH free of SVHC	Yes
EU RoHS Directive	Compliant with Exemptions
Mercury free	Yes
China RoHS Regulation	<a href="#">China RoHS Declaration</a>
RoHS exemption information	<a href="#">Yes</a>