

# Product data sheet

Specifications

SQUARE D



Contactor, Definite Purpose, 40A, 1 pole, 24/24VAC 50/60Hz coil, open

8910DP41V14

Product availability: Stock - Normally stocked in distribution facility

## Main

Product or Component Type	Definite Purpose Contactor
Line Rated Current	40 A
Number of Poles	1P
Pole contact composition	1 NO
Range of Product	DP

## Complementary

Maximum Horse Power Rating	2 hp 115 V AC, 1 phase 5 hp 230 V AC, 1 phase
Locked rotor rated current	240 A 277 V AC 200 A 460 V AC 160 A 575 V AC
[Ue] rated operational voltage	600 V AC
[Uc] control circuit voltage	24 V AC 50/60 Hz
Phase	1 phase
Electrical Connection	Quick connect terminals Box lugs

## Environment

Product Certifications	UL Recognized CSA
------------------------	----------------------

## Ordering and shipping details

Category	US1CP1B21357
Discount Schedule	CP1B
GTIN	785901233053
Returnability	Yes
Country of origin	CN

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.30 in (5.842 cm)
Package 1 Width	2.60 in (6.604 cm)
Package 1 Length	3.40 in (8.636 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package weight(Lbs)	8.160 oz (231.332 g)
Unit Type of Package 2	CAR
Number of Units in Package 2	12
Package 2 Height	5.90 in (14.986 cm)
Package 2 Width	7.20 in (18.288 cm)
Package 2 Length	7.20 in (18.288 cm)
Package 2 Weight	6.440 lb(US) (2.921 kg)

## Contractual warranty

Warranty	18 months
----------	-----------



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
<a href="#">EU RoHS Directive</a>	Compliant with Exemptions

## Use Again

### Repack and remanufacture

Take-back	No
-----------	----

Technical Illustration

Wiring diagram

