

# Product data sheet

Specifications

SQUARE D



Contactor, 8965RO, hoist, reversing, 3hp at 480VAC, 3 phase, 24VAC coil, quick connect terminals. open style

8965RO10V01

Product availability: Stock - Normally stocked in distribution facility

## Main

Product or Component Type	Reversing Hoist Contactor
Maximum Horse Power Rating	1 hp 115 V AC, 1 phase 1.5 hp 230 V AC, 1 phase 3 hp 230 V AC, 3 phase 3 hp 460 V AC, 3 phase 3 hp 575 V AC, 3 phase

## Complementary

Product Certifications	UL Listed CSA
Poles description	3P
[Uc] control circuit voltage	24 V AC 60 Hz
Phase	3 phase
Range of Product	RO

## Ordering and shipping details

Category	US10CP121406
Discount Schedule	0CP1
GTIN	785901032175
Returnability	Yes
Country of origin	MX

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	3.500 in (8.890 cm)
Package 1 Width	4.900 in (12.446 cm)
Package 1 Length	6.500 in (16.510 cm)
Package weight(Lbs)	28.640 oz (811.930 g)

## Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Under investigation
California proposition 65	<b>WARNING:</b> This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No