

Product data sheet

Specifications

SQUARE D



Power distribution block, Linergy, terminal cover for 9080LBA265 or 9080LBC265 blocks

9080LB52

Product availability: Stock - Normally stocked in distribution facility

Main

Range	9080LB
Product	Cover
Fixing Mode	Screwed
Quantity per Set	Set of 5

Complementary

Height	4.5 in (114.3 mm)
Width	5.56 in (141.22 mm)
Depth	0.06 in (1.52 mm)

Ordering and shipping details

Category	US10CP121711
Discount Schedule	0CP1
GTIN	785901139362
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	0.10 in (0.254 cm)
Package 1 Width	4.50 in (11.43 cm)
Package 1 Length	5.50 in (13.97 cm)
Package weight(Lbs)	1.120 oz (31.752 g)
Unit Type of Package 2	CAR
Number of Units in Package 2	20
Package 2 Height	4.70 in (11.938 cm)
Package 2 Width	6.30 in (16.002 cm)
Package 2 Length	7.00 in (17.78 cm)
Package 2 Weight	31.999 oz (907.184 g)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Warranty

18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Take-back	No