


Note:  
- Drawings Not To Scale  
- Drawings Subject to Change Without Notice  
- Dimensions are inches next to [Millimeters]

Part No.:  
**9080LBA161104**

 **SQUARE D**

by **Schneider Electric**

Schneider Electric United States  
North American Division  
Boston One Campus  
800 Federal Street  
Andover, MA 01810, USA  
Phone: +1 8773425173  
Email: CCC@us.schneider-electric.com

| Technical Information: |                         |
|------------------------|-------------------------|
| For Use With:          | Copper or Aluminum Wire |
| Terminal Type:         | Lugs                    |
| Cover:                 | 9080LB11                |
| Service Class:         | C                       |
| UL File:               | E60616 XCFR2            |
| CSA File:              | 70361 6228-01           |
| RoHS:                  | Yes                     |
| CE Marked:             | Yes                     |
| Flammability Rating:   | UL94V-0                 |
| 35mm Track Adapter     | N/A                     |

| Specification:                                       |                   |
|--|-------------------|
| Description:   |                   |
| Ampere Rating:                                       | 115A/90A (Cu/Al)  |
| Max. Voltage Rating:                                 | 600V AC/DC        |
| Number of Poles:                                     | 1                 |
| Wire Range - Main:                                   | (1)#14 to #2 AWG  |
| Wire Range - Branch:                                 | (4)#18 to #10 AWG |
| Short Circuit Current Ratings with Circuit Breakers: | Up to 65 kA       |
| Short Circuit Current Ratings with Fuses:            | Up to 200kA       |