

# Product data sheet

Specifications

SQUARE D



Terminal block, Linergy, mounting track, 35mm DIN rail, no mounting holes, 39.37 inches long

9080MH239

Product availability: Stock - Normally stocked in distribution facility

## Main

Range	9080G
Product	DIN rail
Quantity per Set	Set of 10

## Complementary

Material	Galvanised steel
Height	0.3 in (7.6 mm)
Width	1.38 in (35.05 mm)
Length	39.37 in (1000.00 mm)

## Ordering and shipping details

Category	US10CP521716
Discount Schedule	0CP5
GTIN	785901035688
Returnability	Yes
Country of origin	US

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	0.51 in (1.3 cm)
Package 1 Width	1.30 in (3.3 cm)
Package 1 Length	39.41 in (100.1 cm)
Package weight(Lbs)	11.840 oz (335.658 g)
Unit Type of Package 2	CAR
Number of Units in Package 2	10
Package 2 Height	2.80 in (7.112 cm)
Package 2 Width	2.80 in (7.112 cm)
Package 2 Length	51.40 in (130.556 cm)
Package 2 Weight	8.580 lb(US) (3.892 kg)

## Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

---

Warranty

18 months

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Compliant
REACH Regulation	<a href="#">REACH Declaration</a>
California proposition 65	<b>WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a></b>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No