

# Product data sheet

Specifications

SQUARE D



Terminal block, Linergy, mounting track, 35mm DIN rail, with slotted mounting holes, 10 inches long

9080MH310

Product availability: Stock - Normally stocked in distribution facility

## Main

Range	9080G
Product	DIN rail
Quantity per Set	Set of 10

## Complementary

Material	Galvanised steel
Height	0.3 in (7.6 mm)
Width	1.38 in (35.05 mm)
Length	10 in (254 mm)

## Ordering and shipping details

Category	US10CP521716
Discount Schedule	0CP5
GTIN	785901719397
Returnability	Yes
Country of origin	MX

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	0.30 in (0.762 cm)
Package 1 Width	1.40 in (3.556 cm)
Package 1 Length	10.00 in (25.4 cm)
Package weight(Lbs)	3.840 oz (108.862 g)
Unit Type of Package 2	CAR
Number of Units in Package 2	10
Package 2 Height	2.70 in (6.858 cm)
Package 2 Width	2.70 in (6.858 cm)
Package 2 Length	21.00 in (53.34 cm)
Package 2 Weight	34.399 oz (975.223 g)

## Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

---

Warranty

18 months

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Compliant
REACH Regulation	<a href="#">REACH Declaration</a>
California proposition 65	<b>WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a></b>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No