

Product data sheet

Specifications



DIN rail mounting base - Ø 22 mm units - for control and signalling unit

A9A15151

Main

Range	Acti9
Range of product	Harmony XB4 Harmony XB5 Modicon M221
Quantity per set	Set of 1
Button and pilot light accessory type	Mounting support on DIN rail
Control button component destination	Command unit

Complementary

Material	Insulated material
9 mm pitches	6
Colour code	RAL 9003
Colour tint	White
Diameter	22 mm
Drilling diameter	22.3 mm
fixing mode	By clips
Internal depth	60 mm
Mounting location	Enclosure In cabinet
Mounting support	35 mm symmetrical rail
Product compatibility	XB4 XB5
Net weight	0.04 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.600 cm
Package 1 Width	5.400 cm
Package 1 Length	6.000 cm
Package 1 Weight	28.000 g
Unit Type of Package 2	BB1
Number of Units in Package 2	4

Package 2 Height	8.900 cm
Package 2 Width	9.500 cm
Package 2 Length	18.300 cm
Package 2 Weight	157.000 g
Unit Type of Package 3	S04
Number of Units in Package 3	96
Package 3 Height	30.000 cm
Package 3 Width	40.000 cm
Package 3 Length	60.000 cm
Package 3 Weight	4.812 kg

Contractual warranty

Warranty	18 months
-----------------	-----------

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	90215406-b6bf-44f8-b463-8540d32a6f6b
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: DINP, which is known to the State of California to cause cancer, and DIDP, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
End of life manual availability	No need of specific recycling operations
Take-back	No