


Product data sheet

Specifications



Grounding kit, Heavy Duty safety switch, 30A, Series F1-F3/F5-F7/F2-F7, copper

GTK03C

Product availability: Stock - Normally stocked in distribution facility

Main

Range of Product	Square D
Product or Component Type	Safety switch grounding bar
Series name	Heavy duty

Complementary

Line Rated Current	30 A F1 30 A F5 30 A F7 60 A F1 60 A F3 60 A F5 60 A F7
AWG gauge	AWG 6 copper
Tightening torque	20 lbf.in (2.3 N.m) (AWG 14...AWG 10) 20 lbf.in (2.3 N.m) (AWG 12...AWG 10) 25 lbf.in (2.8 N.m) (AWG 8) 35 lbf.in (4.0 N.m) (AWG 6...AWG 4) 25 lbf.in (2.8 N.m) (2 x AWG 14...2 x AWG 10) 25 lbf.in (2.8 N.m) (2 x AWG 10...2 x AWG 10)

Ordering and shipping details

Category	US10DE100058
Discount Schedule	ODE1
GTIN	785901421825
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	0.50 in (1.27 cm)
Package 1 Width	1.20 in (3.048 cm)
Package 1 Length	1.70 in (4.318 cm)
Package weight(Lbs)	1.280 oz (36.287 g)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile	No need of specific recycling operations
Take-back	No