

Product data sheet

Specifications

SQUARE D



Circuit breaker enclosure, LA, 125A to 400A, 2 and 3 pole, NEMA 12/3R, without knockouts

LA400AWK

Product availability: Stock - Normally stocked in distribution facility

Main

Breaker Compatibility Circuit breaker LAL/LHL/Q4L 125...400 A

Environmental

NEMA Degree of Protection NEMA 12/3R

Ordering and shipping details

Category US10DE100031

Discount Schedule 0DE1

GTIN 785901027195

Returnability Yes

Country of origin MX

Packing Units

Unit Type of Package 1 PCE

Nbr. of units in pkg. 1

Package 1 Height 10.59 in (26.9 cm)

Package 1 Width 14.80 in (37.6 cm)

Package 1 Length 47.40 in (120.4 cm)

Package weight(Lbs) 50.46 lb(US) (22.89 kg)

Contractual warranty

Warranty 18 months

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
Halogen content performance	Halogen free plastic parts product
PVC free	Yes

Use Again

Repack and remanufacture

Circularity Profile	No need of specific recycling operations
Take-back	No