

Product data sheet

Specifications

SQUARE D



Load center accessory, QO/
Homeline, lug kit, neutral, 125A,
AWG 14-2/0, aluminum or copper

LK125AN

Product availability: Stock - Normally stocked in distribution facility

Main

product line	QO
product type	Lug kit

Complementary

ampere rating	125 A
Tightening torque	35 lb.in, AWG 14...AWG 10, aluminium/copper Lugs 35 lb.in, AWG 14...AWG 10, aluminium/copper Lugs 40 lb.in, AWG 8, aluminium/copper 40 lb.in, AWG 8, aluminium/copper Lugs 40 lb.in, AWG 6...AWG 4, aluminium/copper Lugs 50 lb.in, AWG 3...AWG 2/0, aluminium/copper 40 lb.in, AWG 6...AWG 4, aluminium/copper Terminal screw 30 lb.in 50 lb.in, AWG 3...AWG 2/0, aluminium/copper 30 lb.in

Ordering and shipping details

Category	US1DE3A00102
Discount Schedule	DE3A
GTIN	785901379874
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.30 in (3.302 cm)
Package 1 Width	1.50 in (3.81 cm)
Package 1 Length	1.60 in (4.064 cm)
Package weight(Lbs)	1.886 oz (53.479 g)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Compliant with Exemptions

REACH Regulation

[REACH Declaration](#)

California proposition 65

WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No