

# Product data sheet

Specifications

SQUARE D



Panelboard accessory, NQ,  
deadfront kit, branch, 225A, 3  
phase, 54 circuits

NQRPL454L2

Product availability: Non-Stock - Not normally stocked in distribution facility

## Main

Product	Cover plate
Accessory / separate part category	Replacement part

## Complementary

Number of spaces	54
Device Application	panelboard interior
Current Rating	225 A
Tightening torque	45...50 lbf.in (5.08...5.6 N.m) (AWG 6...AWG 2/0) 100 lbf.in (11.3 N.m) (AWG 6...AWG 2/0) 275 lbf.in (31.07 N.m) (AWG 6...350 kcmil) 275 lbf.in (31.07 N.m) (AWG 6...250 kcmil) 275 lbf.in (31.07 N.m) (AWG 4...300 kcmil)

## Ordering and shipping details

Category	US1PE1A00014
Discount Schedule	PE1A
GTIN	785901403555
Returnability	No
Country of origin	MX

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package weight(Lbs)	31.999 oz (907.185 g)

## Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Compliant with Exemptions

REACH Regulation

[REACH Declaration](#)

California proposition 65

**WARNING:** This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

## Use Again

### Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No