



Plug-in unit, I-Line Busway, H-frame, 100A, 3 phase, 3 wire, 600VAC, 18kA, ground

PHG36100G

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Range of Product	I-Line
Product or Component Type	Plug-in unit
Module type	H-Frame

Complementary

[Ue] rated operational voltage	600 V AC 50/60 Hz	
Phase	3 phase	
Busbar description	Ground	
Fuse type	н	
Breaking capacity code	G	
Disconnector device type	Thermal magnetic circuit breaker 100 A 18 kA 600 V Thermal magnetic circuit breaker 100 A 35 kA 480 V Thermal magnetic circuit breaker 100 A 65 kA 240 V	
Level or class	Class 5600	
Wiring configuration	3-wire	

Environment

Product Certifications	UL
	CSA

Ordering and shipping details

Category	US10PE720183	
Discount Schedule	0PE7	
GTIN	3606487248309	
Returnability	No	

Packing Units

Unit Type of Package 1	PCE	
Nbr. of units in pkg.	1	
Package 1 Height	9.02 in (22.9 cm)	
Package 1 Width	12.5 in (31.8 cm)	
Package 1 Length	22.5 in (57.2 cm)	
Package weight(Lbs)	32.01 lb(US) (14.52 kg)	

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Contractual warranty

Warranty

18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

∅ Environmental footprint

Environmental Disclosure

Product Environmental Profile

Use Better

⊗ Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No