

Product data sheet

Specifications

SQUARE D



Safety switch accessory, heavy duty, grounding kit, 200A, Series F5-F7, copper

PKOGTC2

Product availability: Stock - Normally stocked in distribution facility

Main

Range of Product	Square D
Product or Component Type	Safety switch grounding bar
Series name	Heavy duty

Complementary

Line Rated Current	200 A F5 200 A F7
AWG gauge	AWG 4 copper
Tightening torque	35 lbf.in (4.0 N.m) 0.003...0.008 in ² (2.08...5.261 mm ²) (AWG 14...AWG 10) 35 lbf.in (4.0 N.m) 0.008 in ² (5.261 mm ²) (AWG 10) 40 lbf.in (4.5 N.m) 0.013 in ² (8.367 mm ²) (AWG 8) 45 lbf.in (5.08 N.m) 0.02...0.03 in ² (13.30...21.15 mm ²) (AWG 6...AWG 4)

Ordering and shipping details

Category	US10DE100058
Discount Schedule	0DE1
GTIN	785901495994
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.80 in (4.572 cm)
Package 1 Width	0.60 in (1.524 cm)
Package 1 Length	1.20 in (3.048 cm)
Package weight(Lbs)	1.440 oz (40.823 g)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No