



Meter socket, ringless, 1 phase, 3 wire, 5 jaws, Series A-L, lever bypass, jaw release

UTH5213T

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Meter Socket	
Meter socket type	Ringless	
Hub type	A-L ACPL closing plate	

Complementary

Meter socket rated current	200 A
Number of jaws	5 with jaw release
Bypass type	Lever bypass
Phase	1 phase
[Ue] rated operational voltage	600 V AC
Enclosure Material	Steel
Box number	9R
Electrical connection	Lugs 0.5" hex
Service feed location	UG OH
Wiring configuration	3-wire

Environment

Product Certifications	UL Listed	
Enclosure Rating	NEMA 3R	

Ordering and shipping details

	<u> </u>
Category	US10DE400039
Discount Schedule	0DE4
GTIN	785901627821
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	6.10 in (15.494 cm)
Package 1 Width	13.80 in (35.052 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package 1 Length	20.40 in (51.816 cm)
Package weight(Lbs) 21.731 lb(US) (9.857 kg)	

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability

0	Environmental	C1
Y)	Environmentai	tootprint

Environmental Disclosure

Product Environmental Profile

Use Better

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel (Metallic), which is known to the State of California to cause cancer, and Toluene, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No