



Color: ■ black

Similar to illustration

### Notes

Safety Information

Push down the wire jumper until fully inserted!

### Electrical data

#### Ratings per IEC/EN

|   |       |
|---|-------|
| Nominal voltage (III/3)                   | 800 V |
| Rated impulse withstand voltage (III / 3) | 8 kV  |
| Rated current                             | 18 A  |

### Connection Data

#### Connection 1

|                 |                     |
|-----------------|---------------------|
| Solid conductor | 1.5 mm <sup>2</sup> |
|-----------------|---------------------|

### Mechanical data

|   |       |
|---|-------|
| Cable length of push-in type wire jumpers | 60 mm |
|---|-------|

**Material data**

|                      |  |
|----------------------|--|
| Note (material data) | <a href="#">Information on material specifications can be found here</a> |
| Color                | black  |
| Fire load            | 0.004 MJ   |
| Weight               | 2 g  |

**Commercial data**

|                       |                                |
|-----------------------|--------------------------------|
| Product Group         | 2 (Terminal Block Accessories) |
| PU (SPU)              | 100 (10) pcs                   |
| Packaging type        | Box                            |
| Country of origin     | DE                             |
| GTIN                  | 4045454302238                  |
| Customs tariff number | 85444290900                    |

**Product Classification**

|             |                      |
|-------------|----------------------|
| UNSPSC      | 39121421             |
| eCl@ss 10.0 | 27-14-11-40          |
| eCl@ss 9.0  | 27-14-11-40          |
| ETIM 9.0    | EC000489             |
| ETIM 10.0   | EC000489             |
| ECCN        | NO US CLASSIFICATION |

**Environmental Product Compliance**

|                        |                         |
|------------------------|-------------------------|
| RoHS Compliance Status | Compliant, No Exemption |
|------------------------|-------------------------|

**Downloads**




**Environmental Product Compliance**

|   |                   |
|---|-------------------|
| <b>Compliance Search</b>                  |                   |
| Environmental Product Compliance 2009-412 | <a href="#">↓</a> |

**Documentation**

|                 |            |                 |                   |
|-----------------|------------|-----------------|-------------------|
| <b>Bid Text</b> |            |                 |                   |
| 2009-412        | 19.02.2019 | xml<br>2.77 KB  | <a href="#">↓</a> |
| 2009-412        | 28.04.2017 | doc<br>24.00 KB | <a href="#">↓</a> |

### CAD/CAE-Data

| CAD data   | CAE data  |
|--|---|
| 2D/3D Models<br>2009-412  | EPLAN Data Portal<br>2009-412  |
|  | WSCAD Universe<br>2009-412     |

### Installation Notes

#### Commoning



Push down the wire jumper (2009-412) until fully inserted. Lift the jumper with an operating tool for rewiring.

#### Commoning



Push-in type wire jumpers common terminal blocks over longer distances and across multiple levels.